

GEUTEBRÜCK

G-Core
Software Version 4.2.5

Release Notes

GEUTEBRÜCK

Dear business partners,

In the course of an update from G-Core to non-Geutebrück hardware, we would like to point out that the following information must be observed and checked!

For regular Windows 10 installations Intel® has changed the driver model to so-called DCH drivers. These are distributed via the Windows Update and are no longer compatible with the Intel® drivers previously used, so-called legacy drivers. The installation of a DCH driver is not reversible.

The new DCH drivers are used with the following Windows versions:

- Windows 10 1709
- Windows 10 1803
- Windows 10 1809
- Windows Server 2019

If a driver with **version 25.20.100.6444** or newer is installed on one of these systems, it is most likely a DCH driver. The exact version can be checked on the Intel® [homepage](#).

The Geutebrück G-Core Installer contains drivers that are installed on all HW platforms known to us. However, these are legacy drivers. If a legacy driver is installed on a system with new drivers, this can cause lasting damage to your system.

Installations that use Geutebrück hardware or a Geutebrück system image are not affected, as Geutebrück uses a Windows Embedded version (Windows 10 1607). This version does not support the Intel® DCH drivers, so the legacy drivers included in the installation can still be used without restrictions.

Why do Geutebrück install drivers?

Specially tested drivers are installed by us to ensure maximum operational reliability and performance on platforms known to us.

How do I proceed with the installation?

Geutebrück has adapted the G-Core installation to the extent that it checks whether Windows 10 1709/1803 or 1809 are installed on the system and warns the user accordingly, the installation of the Intel® drivers is automatically deselected.

In this case our software will use the already installed new DCH driver. Of course the GPU acceleration is also available with the DCH drivers. If you notice any abnormalities or are unsure about the performance, please contact our service department.

If necessary, the driver version must be checked manually to see if a legacy driver is installed. Only then may the legacy driver be downgraded by the Geutebrück installer by selecting the driver package in the installer.

What do I have to consider after installing with DCH drivers?

As a general rule, if G-Core software is run on your own hardware and Windows installations, you must check how performance and memory consumption are represented and change when Windows updates are performed.

This applies to all Geutebrück products that use GPU Intel® acceleration.

Further information about the drivers can be found on the following page:

<https://www.intel.com/content/www/us/en/support/articles/000031275/graphics-drivers.html>

If you have any questions, the Geutebrück team is at your disposal via the hotline or service@geutebrueck.com.

G-Core Release 4.2.5

Software	Type	Short Description	Detailed Description
Bugfix	G-View	G-View UI	Some input fields in the backup dialog (e.g. bandwidth limit) could not be filled in.
Bugfix	G-Core SAM	SAM - Remote-Dongle-Mode	The connection between the local and remote SAM has been improved. The problem that the database license was not found in cache mode is now solved.
Bugfix	Audit	Image export notification	The image export notification action is now sent again on export. There is an entry in the audit trail as well.
Bugfix	Actiongate	G-Core ActionGate - Behavior when reconnecting	The ActionGate now reconnects after a GeviSoft restart.
Bugfix	IP_Camera	Axis - improved camera support (P1435-LE).	When the camera sends 0 or 1 on the output contacts, they are now processed correctly.
Bugfix	VAM	VAM	Deletion of old records has been improved.
Bugfix	IP-Camera	ONVIF integration	We improved the ONVIF integration, especially when a camera is not sending any time for time synchronization.
Bugfix	SAM	G-Core SAM - Import of SMA was not processed correctly	New SMA files were imported incorrectly under certain circumstances. This resulted in an incorrect dongle hash when the SoftDongle file was read after a restart of the SAM service.
Bugfix	SAM	Edge Recording option	When used Edge recording in GCore, there will be only one GCoreCamConnect option consumed.
Bugfix	SAM	Dongle cache mode improvmenets	Sometimes the cached dongle showed up even the normal dongle was available. This led to the display of two dongles.

Geutebrück supports the following features of the Onvif S Profile (Client) and the Onvif T Profile (Client) :

Features			
General		S	T
System Settings		C	C
User Authentication	WS-Username Token	M	
	Digest Authentication	M	M
User Handling		C	C
Query Services and Capabilities		M	M
Device Discovery		C	M
Network Configuration		C	M
Zero configuration		C	
IP Address Filtering		C	
NTP		C	C
Media Profile Configuration		C	C
Media Transport	(1) RTP/UDP	M	M
	(1) RTP/RTSP/HTTP/TCP	M	M
	RTP/RTSP/HTTPS/TCP	M	C
	RTP/UDP Multicast	C	C
Video			
Video Streaming	MJPEG	M	
	MPEG4	C	
	H.264	C	M
	H.265		M
Video Encoder Configuration		M	M
Video Source Configuration		C	C
Media Profile Streaming Ready out of the box		C	M
Video Streaming	RTSP/RTP	M	M
Imaging Settings			M

Features			
Events		S	T
Event Handling	Pull-point	M	M
	Base-notification	M	
Motion Alarm Events			M
Tampering Event			M
Audio			
Audio Streaming	G.711	C	C
	AAC	C	C
	G726	C	C
Audio Encoder Configuration		C	C
PTZ			
PTZ Move	Absolute	C	M
	Continuous	C	M
	Relative	C	
PTZ Presets		C	C
PTZ - Home Position		C	C
PTZ Configuration		C	C
Additional			
Relay Outputs		C	C
Auxiliary commands		C	C
Focus Control			C
Digital Inputs			C
Metadata Configuration		C	C
Metadata Streaming			C

(1) Client must support at least one of UDP and HTTP.

Function List use the following abbreviations:

M: Mandatory

C: Conditional

= Feature is supported.

= Feature is not supported.

Technical alterations reserved.

GEUTEBRÜCK GmbH

Im Nassen 7-9 | D-53578 Windhagen | Tel. +49 (0)2645 137-0 | Fax-999 | E-mail: info@geutebrueck.com | Web: www.geutebrueck.com